

## 

Power Supply/Charger Board with LED Cable Assembly

Ordering# AL400RLB Kit Contents: AL400ULXB2 with LED Cable Assembly

Altronix AL400RLB power supply/charger converts a 115VAC, 60Hz input into a single 12VDC or 24VDC Class 2 Rated power-limited output. It also offers a suite of features that includes AC fail supervision, battery presence, and low battery supervision. Includes LED cable assembly and LED lens.

| Specifications  |   |   |  |  |
|---|---|---|--|--|
|   | -   |   | Agency Listings (AL400ULXB2)<br>UL:  |  |
| Voltage<br>Input Fuse   | 115VAC 60Hz, 3.5A max.<br>3.5A/250V   | UL294   | Access Control   |  |
| Output<br>Voltage<br>Current<br>Other                         | 12VDC or 24VDC selectable<br>4A/12VDC or 3A/24VDC supply current<br>Short circuit and thermal overload protection<br>Filtered and regulated | UL603<br>UL1069<br>UL1481<br><b>cUL:</b><br>Signal Equipmen   | Burglar Alarm<br>Hospital Signaling and Nurse Call<br>Fire Alarm<br>t CSA C22.2 No.205-M1983 |  |
| Battery Charging  |   | Physical and Environmental  |  |  |
| Type<br>Fuse Rating   | Sealed lead acid or gel type<br>15A/32V<br>Upon AC loss, instantaneous  | Dimensions (L x W x H)<br>Board:<br>7.1" x 4.5" x 1.44" (180.3mm x 114.3mm x 36.6mm)<br>Shipping:<br>10" x 8" x 4" (254mm x 203.2mm x 101.68mm) |  |  |
| Supervision   |   | Weights (approx.):  |  |  |
| AC Failure<br>Battery   | Form "C" contacts<br>Form "C" contacts  | Product:<br>Shipping:   | 0.65 lb. (0.29 kg)<br>0.8 lb. (0.36 kg)  |  |
| Indicators (LED)<br>Input 115VAC is p<br>DC Output<br>Battery | Powered   | Temperature<br>Operating:<br>Storage:<br>Relative Humidity<br>BTU/Hr (approx.):   |  |  |
|   |   |   | 24VDC: 37 BTU/Hr.  |  |

Rev. 04222024

AL400RLB



## AL400RLB

Power Supply/Charger Board with LED Cable Assembly

## Dimensions and Drawing -

Board Dimensions (L x W x H approximate) 7.1" x 4.5" x 1.44" (180.3mm x 114.3mm x 36.6mm) Mounting Holes' Tolerance: +/- 0.04 in. (1mm)

